



Your lithium battery is shipped in shutdown mode. To prepare the battery for use, follow these steps in this order:



1. Connect the 3-pin XLR charger into the 3-pin charging port on the battery box.
2. Plug the charger power cord into the wall electrical outlet.
3. Wait two (2) minutes. Two (2) red LED lights on the charger signify that charging has begun.
4. The batteries are fully charged when the LED on the battery charger is green.

NOTE: If the steps above were not performed in the correct order, unplug the charger cord from both the wall electrical outlet and the scooter, wait one (1) minute, and then repeat the steps above in the order shown.

NOTE: Remove the battery box from the scooter prior to charging when waking the battery up from sleep mode.



Wake Up Instructions

- Every day that you use your mobility device, charge the device overnight, regardless of how short of a ride you took.
- Use the charger that came with your battery for the safest and most efficient charging. Chargers are matched to the type and size of batteries.
- Protect your batteries from extreme heat and cold. It can permanently damage them.
- Do not charge your batteries for more than 24 consecutive hours. Overcharging does not improve performance and actually can have a negative effect.
- **If you do not use your scooter equipped with Lithium Batteries for 25 or more days, the batteries go into a sleep mode.**
 1. To wake up the batteries, remove the battery box from the scooter prior to charging them.
 2. Connect the 3-pin XLR charger into the 3-pin charging port on the battery box
 3. Plug the charger power cord into the wall electrical outlet
 4. Wait two (2) minutes. Two (2) red LED Lights on the charger signify that the charging has begun.
 5. The batteries are fully charged when the LED on the battery charger is green

ONLY use the charger that came with the scooter to charge the batteries in your Endurance!